

Features

Synthesized POCSAG 4-line Alphanumeric Pager

- 4-line alphanumeric display, (20 characters per line)
- Up to 40 inbox message slots
- Up to 24 info slots
- Time and date display
- Time and date stamping
- Unread message reminder alert
- Protect up to 20 inbox, 20 saved messages
- 5 history records in info
- Info alert - individual slot control
- Battery level indicator
- Out-of-range indicator
- Continuous message indicator
- EL back light
- Memory retention
- 1 daily alarm
- Vibrate/ 8 pleasing/ vibrate then audible/ no alert
- 3-speed page scrolling
- Zoom in from 4-line to 2-line display
- Adjustable LCD contrast (0-7 level)
- Low cell reminder
- Priority call
- 4 selectable alert durations; 8sec/16sec/40sec/continuous (PPS option)
- 3 selectable alert modes; All alert, audio only, vibrate/sleep (PPS option)
- Tone message (PPS option)
- PPS programmable group and folders name



Specifications

Model no.	Br802		
Frequency:	VHF (135 - 175MHz), UHF (452 - 468MHz), 900MHz (929-932MHz)		
Code Format:	31/21 POCSAG Code		
Channel Spacing:	12.5 kHz, 25 kHz		
Frequency Deviation:	± 2.5 kHz, ±4.5 kHz		
Paging Sensitivity:	VHF/UHF	900MHz	
EIA Selectivity:	-107 dBm	-104 dBm	(c.. 22.5dB)
EIA Spurious and Image:	55 dB	40 dB	
IM Rejection:	50 dB	40 dB	
Operating temperature:	-10°C to 50°C	5°C to 40°C	
Alert Tone Loudness:	75 dB @ 12 inches		
Battery Type:	1 x Alkaline AA		
Weight (with battery):	65 grams		
Dimensions:	80 x 54 x 19 mm		



RAD DEV FOR HAZ LOC INT SAFE
C.I.,Div1,Gr.CD, Exia, T4



1-888-KELCOM-1
radio@kelcom.com
www.kelcomradio.com

Windsor Location:
1983 Ambassador Drive
Windsor, ON N9C 3R5
Tel: 519-250-9100

Toronto Location:
161 N. Rivermede Rd, #3-4
Vaughan, ON L4K 3N6
Tel: 905-761-6070